

SCORE & FOLD

# ARTEMIS

## AUDIO BODYWIRE WITH ON BODY RECORDER

removable  
mini SD card



direct download to computer



audio tracks transfer to  
Windows® PC, plays with  
any standard PC media  
player application

Outside Cover  
Inside Fold

diecut

Specifications	
Power (RF)	500 mW into 50 ohm load (high)
Controls and Indicators	• 10 position rotary channel/mode switch • Sliding ON/OFF power switch • Bi-color Status LED
Connectors	Mic/antenna, combination external mic/power/ programming and multi-pin connector
Frequency Stability	Within +/- 2.5 ppm over -30° C to +65° C
Minimum Tuning Step	N/A: Transmitter can be programmed to any channel within specified frequency band
Deviation	5 KHz (wide) or TIA/EIA-102 compliant 2.5 KHz (narrow), programmed by channel
Microphone	Electret-fet
Spurious and Harmonics	-50 dBc max
Operating Temp Range	-30° C to +70° C
Operating Voltage Range	3.5-8 VDC
Power Sources	4 AAA Batteries
Battery Life	4 Hours minimum in Transmit/Record mode 8 Hours in Record only mode
Dimensions	Unit .188 lbs / Unit and Batteries .288 lbs 2.27" W x 3.56" L x .515" D
Weight	TIA/EIA-102 - Analog and Digital Modes
NTIA Compliant	



**DTC COMMUNICATIONS, INC. 800-233-8639**  
486 Amherst Street • Nashua, New Hampshire 03063 • 603-880-4411

- Kit Components**
- 8 AAA Batteries
  - Noodle Antenna
  - Mic/Antenna
  - Programming Cable & Software
  - MiniSD Card to USB Port Adapter
  - SD Card Adapter
  - 512MB MiniSD Card and
- MODEL T-2350-DW-SD**  
**Digital & Digital Encrypted Transmitter/Recorder**
- MODEL T-2350-SD**  
**Analog Transmitter/Recorder**

SCORE & FOLD



SCORE & FOLD

SCORE & FOLD

# ARTEMIS Audio Transmitter

This miniature audio transmitter has an internal mini-SD card recording capability. You can now record up to eight hours of audio on a standard mini-SD card, depending on the capacity of your card. Downloading the audio from the mini-SD card is quick and convenient, using a card module that connects right to your PC. Simply slide the mini-SD card into its holder, insert into the SD card module into your PC, and your audio file will be transferred as a .WAV file right on your computer. There is no special software to purchase. Your files will contain the date and time stamp of your event and can be easily transferred to other removable media.

2.3" x 3.6" x 0.5"

## Features

- 500 mW power output.
- Up to eight hours audio record capability on a mini-SD card.
- Downloads audio directly to a PC with no special software requirements.
- Available for analog, digital and digital encrypted modes.
- Generates voice messages with SD card capacity on power up.
- Operates on 4 AAA alkaline batteries.
- Ultra small size of only 2.3" x 3.6" x .5"
- Internal and external microphone options



THE THINNEST BODYWIRE RECORDER

## PROJECT 25 COMPATIBLE

- ✓ **ANALOG**
- ✓ **DIGITAL**
- ✓ **DIGITAL ENCRYPTED**

### Compatible with all DTC Receivers and P-25 Team Radios

The ARTEMIS Bodywire can be configured for Analog, Digital, and Digital Encrypted transmissions. Due to the modular design and advanced software technology you can purchase an ARTEMIS Analog Bodywire with SD Card Record capabilities for less than other Audio Record/Transmitters on the market. As your department migrates to digital and encryption technology, a software FLASH upgrade will enhance your hardware to meet these needs.



SUPPLIED  
**512 MB**  
MEMORY  
CARD



FOUR AAA BATTERIES  
PROVIDE UP TO  
**8 HOURS**  
OF OPERATION

see specifications on back panel.

actual size



SCORE & FOLD

SCORE & FOLD

diecut

SCORE & FOL

SCORE & FC